

# USER'S MANUAL ADDENDUM

## Matched Pair Bridges

Certain AvaLAN radios are sold as matched pairs, pre-configured as a wireless Ethernet bridge. The manual supplied with the pair does not include information about the pair configuration, hence this addendum.

This addendum applies to these products:

AW900xTR-PAIR	AW2400xTR-PAIR	AW5800xTR-PAIR
AW900iTR-PAIR	AW2400iTR-PAIR	
AW900xTP-PAIR	AW2400xTP-PAIR	AW5800xTP-PAIR

The pair configuration as shipped from the factory consists of these features:

1. One unit of the pair is configured as an Access Point and the other is configured as a Subscriber Unit.
2. The Access Point is given the IP Address 192.168.17.17.
3. The Subscriber Unit is given the IP Address 192.168.17.18.
4. User-specified encryption keys are disabled and the two radios are keyed to each other using the "Auto-Key" method.
5. RF Channel selection is set to automatic mode.

If these configuration parameters work for you in your system, you need only to connect antennas, power and LAN and the pair should work transparently, looking just like an Ethernet cable.

If you need to change any of the pair's parameters, you may use the browser interface as described in the accompanying manual. You might need to do this if you need to set the pair to a particular channel, or you wish to provide your own encryption keys. If the default IP Addresses won't work in your system, the best way to change them is by using the ipfinder utility described in the manual and downloadable from [www.avalanwireless.com](http://www.avalanwireless.com).

In case of difficulty, you may find additional help under the Support tab on our website or by contacting AvaLAN Technical Support using the information in the manual.

Revision 08.11.2010